

SBMS EIRP-MDS MW Tune Up

Sat. 22 JULY 2017

10 GHz: Range = 220 Ft.
FSPL = 89.3 dB

System Losses = 18.0 dB
EIRP Amp Gain = 15.2 dB

WG Flange = 5 dBi
MDS Attenuator 30 dB

Callsign	Reflector Size (inches)	Ant. Effic. (%)	Caic. Ant. Gain (dBi)	EIRP TEST		EIRP Reading (dBm)	Meas. EIRP (dBm)	meas. vs. Calc. (dB)	Conditions	MDS TEST		
				Radio Output (dBm)	Calc. EIRP (dBm)					Sig. Gen. Out (dBm)	MDS Atten. (dB)	MDS SCORE
(DATA)	(DATA)	(DATA)	RESULT	(DATA)	RESULT	(DATA)	RESULT	(Delta)		(DATA)	(DATA)	RESULT
K6YAC	12.0	0.55	28	27.0	55	-49.5	38	-17.2	PRIME	-29	30	-72
KK6MXP	24.0	0.55	34	36.6	70	-17.6	70	-0.9	PRIME	-53	30	-96
WB6NOA	42.0	0.55	39	31.7	70	-34.6	53	-17.8	PRIME	-44	30	-87
AF6NA	32.8	0.64	37	43.6	81	-6.8	80	-0.4	OFFSET	-57	30	-100
W6IEE	26.6	0.55	35	24.0	59	-33.4	54	-5.0	PRIME	-38	30	-81

FSPL = Free Space Path Loss

EIRP Readings taken /w/ power meter or Spectrum Analyzer in peak mode

Meas. EIRP = Reading + Sys Loss + FS Path Loss - Amp Gain - WG Flange Gain

Ant Gain Calc = $10 \times \text{LOG}(((4 \times \text{Pi} \times (\text{Pi} \times \text{R Squared})) \times \text{Efficiency \%}) / \text{LAMBDA Squared})$

MDS Signals Generated @ 144 MHz with VHF / UHF Signal Generator

MDS Score = Sig. Gen. Output - Atten. - Sys. Loss + WG Gain

System Losses = Test Fixture Conversion / Insertion Loss + 300 ft. Cable Loss

F.S. Path Loss = $37.5 + 20 \times \text{LOG}(\text{Dist in feet}) + 20 \times \text{LOG}(\text{Freq MHz})$ - same as prior years = 89.3 dB @ 10.368 GHz

300 ft. Cable Loss = 7.5 dB @ 144 MHz

Open WR-90 Gain assumed to be 5 dB